



Raccord équerre mâle conique


MATIÈRE

- Laiton.

FOURNITURE

- Raccord.

- Ecrou.

- Olive.

Référence
Exemple de commande H32-L-4-1/8-CO

	d ₁	d ₂	l ₁ max	l ₂	h ₁	s ₁	s ₂
H32-L-4-1/8-CO	4	1/8"	19	9,5	17	10	8
H32-L-4-1/4-CO	4	1/4"	19	11	20	10	10
H32-L-5-1/8-CO	5	1/8"	21	11	17,5	12	8
H32-L-5-1/4-CO	5	1/4"	22	12	21,5	12	10
H32-L-6-1/8-CO	6	1/8"	22	11	18	13	8
H32-L-6-1/4-CO	6	1/4"	22	12	21,5	13	10
H32-L-8-1/8-CO	8	1/8"	28	15	18,5	14	10
H32-L-8-1/4-CO	8	1/4"	28	15	22	14	10
H32-L-8-3/8-CO	8	3/8"	28	15	24	14	12
H32-L-10-1/4-CO	10	1/4"	30	14,5	25	19	12
H32-L-10-3/8-CO	10	3/8"	30	14,5	25,5	19	12
H32-L-10-1/2-CO	10	1/2"	36	21	32	19	19
H32-L-12-1/4-CO	12	1/4"	30	15	26	22	15
H32-L-12-3/8-CO	12	3/8"	30	15	27	22	15
H32-L-12-1/2-CO	12	1/2"	36	21	32	22	19
H32-L-14-3/8-CO	14	3/8"	35	18	30	24	19

	d ₁	d ₂	l ₁ max	l ₂	h ₁	s ₁	s ₂
H32-L-14-1/2-CO	14	1/2"	35	18	32	24	19
H32-L-15-3/8-CO	15	3/8"	35	18	30	24	19
H32-L-15-1/2-CO	15	1/2"	35	18	32	24	19
H32-L-16-3/8-CO	16	3/8"	39	21	30	27	19
H32-L-16-1/2-CO	16	1/2"	39	21	33,5	27	19
H32-L-16-3/4-CO	16	3/4"	41	23	36,5	27	23
H32-L-18-1/2-CO	18	1/2"	41	21,5	35,5	30	23
H32-L-18-3/4-CO	18	3/4"	41	21,5	36,5	30	23
H32-L-20-1/2-CO	20	1/2"	42	21,5	36,5	32	23
H32-L-20-3/4-CO	20	3/4"	42	21,5	38	32	23
H32-L-22-3/4-CO	22	3/4"	50	30	40	36	27
H32-L-22-1-CO	22	1"	50	30	44	36	27
H32-L-25-3/4-CO	25	3/4"	54	30	43	41	27
H32-L-25-1-CO	25	1"	54	30	44	41	27
H32-L-28-3/4-CO	28	3/4"	54	30	46	42	32
H32-L-28-1-CO	28	1"	54	30	48	42	32